



CAT-20

# BR1 Pro

Here LTE gets Sonic

Wi-Fi just got better

Connect multiple devices simultaneously, and experience faster throughput speeds and better bandwidth congestion with the latest Wi-Fi 6, all with less interference.



SpeedFusion Ready


Enable the endless possibilities of SpeedFusion technology just by simply connecting to SpeedFusion Cloud from wherever you are.





### Performance Boost

The BR1 Pro has been boosted with a CAT-20 modem which can achieve speeds of up to 800% faster than the original BR1 Pro.



- Status
- Wi-Fi
- Cellular


### Hardcore Capabilities


The BR1 Pro comes equipped with a 2.5Gbps Ethernet port, making it compatible for your network devices to run at their designated speeds without limitations.



### Deploy Anywhere

Certified toughness and wide operating temperatures mean you can just deploy, forget, and enjoy the benefits.





## Specifications

|  |  |                              |   |
|--|--|------------------------------|---|
| <b>WAN Interface</b>                                     | 1x 10/100/1000/2500M Ethernet <sup>1</sup><br>1x LTE-A Pro Modem with Redundant SIM Slots  | <b>Antenna Connectors</b>    | 4x SMA Cellular Antenna Connectors<br>2x RP-SMA Wi-Fi Antenna Connectors<br>1x SMA GPS Antenna Connector  |
| <b>LAN Interface</b>                                     | 2x 10/100/1000M Ethernet   | <b>Power Input</b>           | 10 - 30V  |
| <b>Wi-Fi Interface</b>                                   | Simultaneous Dual-Band (2.4GHz / 5GHz)<br>Wi-Fi 6, 2X2 MU-MIMO<br>Wi-Fi WAN and/or AP      | <b>Power Consumption</b>     | 8 W (nominal), 19 W (max.)  |
| <b>SpeedFusion features</b>                              | Hot Failover <sup>2</sup> , WAN Smoothing <sup>2</sup> ,<br>Bandwidth Bonding <sup>2</sup> | <b>Dimension</b>             | 5.78 x 5.08 x 1.15 inches / 146.8 x 129 x 29.3 mm   |
| <b>Number of SpeedFusion VPN Peers</b>                   | 2 / 5 <sup>3</sup>   | <b>Weight</b>                | 1.5 pounds / 680 grams  |
| <b>Features</b>  | Drop-in Mode<br>Load Balancing/Failover<br>Ignition Sensing                                | <b>Operating Temperature</b> | -40° - 149°F / -40° - 65°C  |
| <b>Router Throughput</b>                                 | 1 Gbps   | <b>Humidity</b>              | 15% - 95% (non-condensing)  |
| <b>SpeedFusion VPN Throughput</b>                        |  | <b>Certifications</b>        | FCC, CE, RoHS<br>E-Mark (Motor Vehicle) <sup>6</sup><br>EN 61373 Shock and Vibration Resistance <sup>6</sup><br>EN 50155 Railway Applications - Electronic Equipment used on Rolling Stock<br>EN 61000 Electromagnetic Compatibility<br>EN 45545-2 Railway applications - Fire protection |
| <b>- No Encryption</b>                                   | 400 Mbps   | <b>Package Content</b>       | 1x MAX BR1 Pro CAT-20<br>4x LTE/5G Antennas (ACW-234)<br>2x Dual Band Wi-Fi Antennas (ACW-341)<br>1x GPS Antenna (ACW-232)<br>1x 12V2A Power Supply (ACW-632)   |
| <b>- 256-bit AES</b>                                     | 200 Mbps   | <b>SIM Card Size</b>         | Nano-SIM (4FF)  |
| <b>Recommended Users</b>                                 | 1-150  | <b>Warranty</b>              | 1-Year Limited Warranty   |
| <b>AP Controller</b>                                     | Standard <sup>4</sup>  |                              |   |
| <b>Maximum Number of AP Supported</b>                    | 30 <sup>4</sup>  |                              |   |
| <b>Cellular Data Rate <sup>5</sup> (Downlink/Uplink)</b> | CAT-20: 2 Gbps / 211 Mbps  |                              |   |

<sup>1</sup> The WAN port can act as a LAN port if needed.

<sup>2</sup> Requires PrimeCare Subscription, complementary for the first year.

<sup>3</sup> 2 SpeedFusion VPN Peers are enabled by default. <sup>5</sup> SpeedFusion VPN Peers are enabled with PrimeCare Subscription, complimentary for the first year.

<sup>4</sup> Will be supported in a future firmware upgrade.

<sup>5</sup> Theoretical maximum data rates.

<sup>6</sup> Certifications Pending.

## Ordering Information

---

| Product Code  | Regions               | LTE Bands  | 3G Bands                          |
|---|-----------------------|--|-----------------------------------|
| MAX-BR1-PRO-GLTE-S-T-PRM<br>Embedded Modem(s):<br>1x LTE-A Pro (CAT-20) | Compatibility: Global | B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39, B40, B41, B42, B46, B48, B66, B71 | HSPA+: B1, B2, B3, B4, B5, B8, B9 |

## Featured Add-on

---

| Product Code       | Description                  |
|--------------------|------------------------------|
| PRM-MAX-BR1-PRO-1Y | 1-Year PrimeCare for BR1 Pro |
| PRM-MAX-BR1-PRO-2Y | 2-Year PrimeCare for BR1 Pro |
| PRM-MAX-BR1-PRO-4Y | 4-Year PrimeCare for BR1 Pro |